

P R O 8 5 0

850



PRO850™ Wireless Intercom System

HME
®

Customer Driven

Go the distance in wireless performance.



System Highlights

- > Frequency agile/Exceptional operating range
- > Wide frequency response with low distortion
- > Simultaneous dual-channel operation
- > Automatic frequency selection
- > PC and PDA interface

User-Friendly Displays & Menus



PDA850 - Allows beltpac status to be checked and configuration set without returning the unit to the base station.



Talk Status - Displays the talk status of all receivers at a glance. If a user is talking, that user's name is clearly shown.



Receiver Controls - Press the "Receiver Quick Menu" button to gain instant access to receiver controls.

Why choose the new *PRO850* Wireless Intercom System from HME? Simply because you can do more with the *PRO850* than any comparable system on the market. With the *PRO850*, you'll get exceptional operating range, cutting-edge features, and the flexibility to configure and expand the entire system to meet your unique intercom needs. Innovative features like PC and PDA interface, automated power control, simultaneous dual-channel interface, Wireless ISO — plus all the standard capabilities — give you more operating power and flexibility to achieve the best performance. Combine all that with a ruggedly-constructed design, the *PRO850* provides the utmost reliability and sound quality. More value. Better performance. Greater reliability. The *PRO850* is the ultimate solution for all your intercom needs.



BASE STATION

More Operating Power

- **Frequency agility** enables you to operate the PRO850 within the 470-740 MHz UHF band. These synthesized frequencies can be selected in 25 kHz increments over each 18 MHz operational band so you can easily choose from 720 different transmit and 720 receive frequencies.
- **User-friendly graphical interface** on the base makes it easy to set up the system and obtain status information using the LCD display and menu keys. Pull-down menus on the LCD provide fast, easy access to all system features. Menus are organized by status, audio-level monitoring, system configuration, and system information. Simple navigation buttons and multi-function rotary knob facilitate the setup and access of desired features.
- **PC interface** using HME's PC850 Software lets you configure the entire PRO850 System and manage configuration files from the convenience of your PC via the RS-232 serial or USB port.
- **Expandable system** allows you to configure the PRO850 to meet your communication needs. A standard PRO850 System comes with four beltpacs and a base station. By linking several base stations to provide additional receivers, up to 16 users can communicate with each other in full-duplex operation.
- **Automated beltpac output power control** helps optimize the system operating power. The base station automatically configures beltpac settings and calibrates the power level for each beltpac, depending on its distance from the base. This eliminates base receiver overload and extends the beltpac battery life.
- **Intermodulation-free frequency groups** have been pre-configured to help you easily scan and select the best, interference-free frequency groups when you set up the PRO850. The savvy user can also configure additional frequency groups for a quick recall.
- **Alert relay output** provides a configurable set of contacts that can respond to problem conditions or to beltpac user requests.
- **Audio digitally mixed and routed under user control** allows any combination of inputs to be mixed and delivered to any output. These settings can be preset and saved to provide different mix configurations for different shows.
- **Remotely "unlatch" beltpacs from transmitting** at the base to stop a rogue beltpac that's been left transmitting without having to locate the beltpac.

BELTPAC

More Flexibility

- **PDA interface** provides a convenient method to configure beltpac frequencies and functions through a built-in IrDA port using a Palm-OS PDA and PDA850 Tools.
- **Beltpac controls are configurable** for multiple transmit modes. Separate talk buttons for each channel can be configured for "push-to-talk" or "push-to-enable" operation. Buttons not configured for transmitter control can be configured for party-line selection, paging, ISO, alert and call functions.
- **Individual volume controls** allow beltpac users to adjust and mute the volume. The MASTER and Auxiliary Volume Controls provide a push-to-mute function so you can temporarily mute a channel while keeping previous volume settings.
- **Dual-channel access** allows users to choose from two hardwired intercom channels. Simultaneous dual-channel access is obtained using the optional 2nd receiver module.
- **Alert and page relay closures** allow you to remotely control external devices from the beltpac.
- **Channel lockout** enables multiple beltpac users to share the same operating frequency and automatically disable a beltpac's ability to transmit if another user is already transmitting on that frequency.
- **Low battery alert** informs the user through the headset and base station that the beltpac batteries are low.
- **Versatile headset connector** allows use of standard 4-pin male connector or field-install of a 5-pin female XLR connector. The beltpac auto-detects the microphone type.
- **Detachable antennas** with strong, threaded connectors make storage and shipping easy.
- **Auxiliary audio input** allows a separate audio source, such as an IFB receiver, to be heard through the beltpac headset and controlled by the beltpac volume controls.
- **LED blackout mode** enables crew members to work on a darkened stage without tell-tale lights being visible to the audience.
- **Automatic status reporting to base** keeps the technical crew informed of the battery condition and which users are talking.



Base Station Specifications

General

Frequency Range: 470-608 MHz, 614-740 MHz in 18 MHz TX and RX Bands
 Frequency Response: 50 Hz to 10 kHz
 Power Requirements: 100-240 VAC, 50-60 Hz or 12-14 VDC
 Size: 19" x 1.72" x 11.75" (1-RU)
 (48.26cm x 4.37cm x 29.8cm)
 Weight: <11 lbs (<5 kg)
 Tx & Rx Antenna: 1/4-Wave (Supplied), BNC Connector
 4-Wire I/O: RJ45, 600Ω Balanced, Level Adjustable,
 Simultaneous Operation with 2-Wire
 2-Wire I/O: XLR-3F, Externally-Switchable RTS® or ClearCom®
 Mode, 200Ω, Level Adjustable, Null Adjustable
 Auxiliary Input: XLR-3F/1/4" Phone Combo Jack, 600Ω Balanced,
 Level Adjustable
 Aux & Page Output: XLR-3M, 600Ω Balanced, Level Adjustable
 Page & Alert Relay: 2 Four-Pin Phoenix, 2A @ 30 VDC Max
 Beltpac Interface: RJ10, RS-232
 PC Interface: DB9, RS-232, 38400 baud
 USB Interface: USB B-Type Receptacle, USB 1.1 Compliant
 External Control Interface: RJ45, RS-422
 Headset Connector: XLR-4M (Optional Field-Installable XLR-5F)
 Mic Input: Auto-Detect, Low Impedance Dynamic or Electret
 Headset Output: Stereo - 160 mW per Side, Mono - 250 mW
 Front Panel Controls: Power Switch with Indicator
 Menu Navigation Keys
 Receiver Quick-Menu Keys
 Rotary Knob for Adjustments
 Headset Channel Select & PTT
 Front Panel Indicators: Graphic LCD
 3 Wired System Status LEDs
 4 Receiver Status LEDs
 Headset Channel Select & Talk LEDs
 Rear Panel Controls: 2-Wire Channel Line Null
 RTS®/ClearCom® Mode Switch

Transmitter

Type: 720 Synthesized, 25 kHz Channel Steps
 Transmit Power: 240, 100, 10 or 1 mW Configurable
 Modulation Type: FM
 Deviation: 50 kHz
 Frequency Stability: 10 ppm
 Harmonics/Spurious: Exceeds FCC Specifications

Receiver

Type: 720 Synthesized, 25 kHz Channel Steps
 RF Sensitivity: <1µV for 20dB SINAD
 Squelch Threshold: Front Panel Adjustable
 Image Rejection: >70dB
 Squelch: Data Channel Coded Plus Carrier Signal Level
 Squelch Quieting: 90dB
 Frequency Stability: 10 ppm
 Distortion: <1% at Maximum Deviation

All specifications are subject to change without notice.
All trademarks are the property of their respective owners.

HM Electronics, Inc.

14110 Stowe Drive, Poway, CA 92064 | USA
www.hme.com | Tel: (858) 535.6060

© 2005 HM Electronics, Inc. The HME logo and product names
 are registered trademarks of HM Electronics, Inc. All rights reserved. LT05-03

Beltpac Specifications

General

Frequency Range: 470-608 MHz, 614-740 MHz in 18 MHz TX and RX Bands
 Antenna Type: Flexible 1/4-Wave, Field-Replaceable
 Frequency Response: 50 Hz to 10 kHz
 Battery Requirements: 6 "AA" Alkaline Cells (Optional NiMH)
 Battery Life: PTE: Up to 9 Hours (Alkaline)
 PTT: Up to 15 Hours (Alkaline)
 Size: 5.75" x 4.38" x 2.31" (14.6cm x 11.13cm x 5.87cm)
 Weight: 16 oz (0.45 kg) with Batteries
 Base Interface: RJ10, RS-232
 PDA Interface: IrDA
 Auxiliary Input: Connector: 1/8" Miniature Phone Jack
 Impedance: 8kΩ, Input Level: 100 mV
 Overrides Optional 2nd Receiver If Installed.
 Headset Connector: XLR-4M (Optional Field-Installable XLR-5F)
 Mic Input: Auto-Detect, Low Impedance Dynamic or Electret
 Headset Output: 200 mW @ 1% THD into 50Ω
 Controls: Main Volume Control with Power Switch and Push-to-Mute, 2nd RCVR/AUX Volume Control with Push-to-Mute, 4 Mode/Function Switches
 Microphone Gain Adjustment
 Indicators: Power/Low Battery LED
 Transmit LED & 4 Channel/Status LEDs

Transmitter

Type: 720 Synthesized, 25 kHz Channel Steps
 Transmit Power: 100, 50, 10 or 1mW, Fixed Output/Automatic Control
 Transmission Modes: Push-to-Talk (PTT), Push-to-Talk-Shared (PTS), or Push-to-Enable (PTE).
 May Be Configured for Momentary or Latch Mode.
 Modulation Type: FM
 Deviation: 50 kHz
 Frequency Stability: 10 ppm
 Harmonics/Spurious: Exceeds FCC Specifications

Receiver

Type: 720 Synthesized, 25 kHz Channel Steps
 RF Sensitivity: <1µV for 20dB SINAD
 Squelch Threshold: User Configurable
 Image Rejection: >70dB
 Squelch: Adjustable Carrier Signal Level
 Squelch Quieting: 80dB
 Frequency Stability: 10 ppm
 Distortion: <1% at Maximum Deviation

Options/Accessories

AC850 Four-Port Battery Charger
 BAT850 NiMH Rechargeable Battery Pack
 Beltpac 2nd Receiver Module
 PC850: PC-Based Application Tools
 PDA850: Palm OS PDA-Based Application Tools

Distributed by: